

.SE EPP Rules, Policies and Protocol description

Version 19

Document number: JUR-0001-19-O-EN

© IIS - The Internet Foundation in Sweden IIS



Document control

Document information and security

Revisions

Date	Version	Description
2008-10-10	1.1	<ul style="list-style-type: none"> • Fix xml namespaces • VATNO format • Added <iis:clientDelete/> information • Add <msgQ/> to poll request answer
2008-10-28	2	<ul style="list-style-type: none"> • Fixed examples • Fixed double quotes in markup • Some formatting
2008-11-04	3	<ul style="list-style-type: none"> • Fix notify tags
2008-11-12	4	<ul style="list-style-type: none"> • Fixed xml namespace prefixes • Fixed period create/renew domain
2008-11-19	5	<ul style="list-style-type: none"> • <poll/> example response fixed
2008-12-16	6	<ul style="list-style-type: none"> • More XML fixes
2009-01-13	7	<ul style="list-style-type: none"> • Fix RFC numbering DNSSec
2009-02-12	8	<ul style="list-style-type: none"> • Dates not allowed to specify time zone • Transfer removes <iis:clientDelete/> • Fix <domain:update example, only one secDNS tag allowed.
2009-03-12	9	<ul style="list-style-type: none"> • Fix <iis:orgno/> description • Fix contact update examples
2009-09-29	10	<ul style="list-style-type: none"> • Date/time format for responses • <iis:transfer/> extensions • Create/renewal period • clID max 16 chars • <domain:info/> extensions • RFC updates • lis namespace update
2009-11-20	11	<ul style="list-style-type: none"> • Domain:period changed • Connection limits updated
2009-12-04	12	<ul style="list-style-type: none"> • Description of transfer extensions
2011-01-20	13	<ul style="list-style-type: none"> • RFC 5910
2011-03-01	14	<ul style="list-style-type: none"> • June 2011 release
2012-10-15	16	<ul style="list-style-type: none"> • Merged Protocol Description and Rules and Policies and changed names to EPP Rules, Policies and Protocol Description. • Removed Contact Info for unauthorized clients • Added info about EPP Test, changes in Rules and policies and EPP Forum • Added info about Valid IDN characters and Valid postallInfo characters • Add RFC 3492 for Punycode.

Date	Version	Description
2015-04-13	17	<ul style="list-style-type: none">• Change to 1-63 characters a-z,0-9,-.• Removed the reference to registrarsse's EPP Forum.
2017-08-24	18	<ul style="list-style-type: none">• Removed mention about extra info in 6.5 being returned for only sponsoring client• Changed to new logo• Added 8.2 about changing address on a host object with glue records
2017-09-27	19	<ul style="list-style-type: none">• Changed information in 2.5• Updated information in 6.5 about domain:roid• Changed 6.8 since the delete command now is supported• Updated 6.9 regarding PendingDelete• Created 7.1.11 with information about <contact:authInfo>• Added some information in 7.4• Updated 7.1 regarding format for <contact:id/>

List of contents

1	Introduction	6
1.1	This document	6
1.2	Abbreviations & Definition of words	6
1.3	References	6
1.4	About IIS.....	6
2	Overview	7
2.1	General.....	7
2.2	XML.....	7
2.3	Rules and Policies	7
2.4	Server Usage	8
2.5	Client Certificate	8
2.6	Data format	8
2.7	RFC 5910 DNSSec Extension	8
2.8	.se EPP Test platform.....	8
2.9	Changes in Rules and Policies	9
2.10	EPP Support.....	9
3	Response	10
4	Session Commands	11
4.1	Hello and Greeting.....	11
4.2	Login.....	12
4.3	Logout	13
5	Message commands	14
5.1	Poll	14
6	Domain Objects	17
6.1	Domain Rules and Policies	17
6.2	DNSSEC.....	18
6.3	Valid Domain Name characters	18
6.4	Check.....	20
6.5	Info	20
6.6	Transfer.....	22
6.7	Create.....	23
6.8	Delete	24
6.9	Update.....	24
6.10	Renew	26
7	Contact Objects	27
7.1	Contact Rules and Policies	27
7.2	Character sets for postallInfo	29
7.3	Check.....	34
7.4	Info	34
7.5	Transfer.....	36
7.6	Create.....	36
7.7	Delete	37
7.8	Update.....	37
7.9	Renew	38



8	Host Objects	39
8.1	Host Rules and Policies.....	39
8.2	Address update with glue record	39
8.3	Check.....	39
8.4	Info	40
8.5	Transfer.....	41
8.6	Create.....	41
8.7	Delete	42
8.8	Update.....	42
8.9	Renew	43

IIS[.SE](#)



1 Introduction

1.1 This document

This document is meant to give a brief overview over the existing EPP commands and policies of the .se EPP-server.

1.2 Abbreviations & Definition of words

EPP	<i>Extensible Provisioning Protocol</i> , “An XML text protocol that permits multiple service providers to perform object provisioning operations using a shared central object repository” ([1]).
DNSSEC	<i>Domain Name System Security Extensions</i> .
Sponsoring Client	The registrar responsible for an object in EPP.

1.3 References

- [1] Extensible Provisioning Protocol (EPP), IETF RFC 5730.
- [2] Extensible Provisioning Protocol (EPP) Domain Name Mapping, IETF RFC 5731.
- [3] Extensible Provisioning Protocol (EPP) Host Mapping, IETF RFC 5732.
- [4] Extensible Provisioning Protocol (EPP) Contact Mapping, IETF RFC 5733.
- [5] Domain Name System (DNS) Security Extensions Mapping for the Extensible Provisioning Protocol (EPP), IETF RFC 4310, IETF RFC 5910
- [6] Extensible Provisioning Protocol (EPP) Transport over TCP, IETF RFC 5734.
- [7] Guidelines for Extending the Extensible Provisioning Protocol (EPP), IETF RFC 3735
- [8] E.164 Number Mapping for the Extensible Provisioning Protocol (EPP), IETF RFC 4114
- [9] Punycode: A Bootstring encoding of Unicode for Internationalized Domain Names in Applications (IDNA), IETF RFC 3492

1.4 About IIS

IIS (The Internet Infrastructure Foundation) is responsible for the Internet top-level domain for Sweden. As the central registry, IIS manages domain name registrations and the administrative and technical operation of the national domain name system for .se.

IIS is an independent non-profit organisation, supporting the positive development of the Internet in Sweden. Through IIS Internet Fund, the Foundation annually donates means to projects supporting the development and utilisation of the Internet.

2 Overview

2.1 General

The purpose of this document is to describe the existing EPP commands and policies of the .se EPP-server. Readers are assumed to be familiar with the EPP-protocol as we will not cover this in this document. Please refer to the RFC:s listed in section 1.3 for more information on the EPP-protocol.

The EPP-commands are, in this document, divided into three main categories, session commands (section 4), message commands (section 5) and object commands (sections 6-8).

Session commands are used for session management. These include a command to initiate a session (login), end a session (logout) and the hello command used to gain information about the server.

Message commands are restricted to the poll command used to fetch and acknowledge queued messages.

Object commands are used to query and transform objects at the registry. There are three kinds of objects used by the .se EPP server; domain objects, contact objects and host objects. Domain objects contain all data necessary to represent internet domain names, contact objects contains all necessary data to represent persons or companies and host objects contains all data necessary to represent name servers in the registry.

The object commands contains commands for checking if objects exist, to query for information about objects, to create/update/delete objects etc. Some of these commands use EPP extensions to facilitate extra information or extra services for the object.

Readers should also have a look at the EPP FAQ for further details.

2.2 XML

All through this documentation we will use descriptive prefix names for all object namespaces:

xmlns:host	”urn:ietf:params:xml:ns:host-1.0”
xmlns:contact	”urn:ietf:params:xml:ns:contact-1.0”
xmlns:domain	”urn:ietf:params:xml:ns:domain-1.0”
xmlns:secDNS	“urn:ietf:params:xml:ns:secDNS-1.0”
xmlns:secDNS	“urn:ietf:params:xml:ns:secDNS-1.1”
xmlns:iis	”urn:se:iis:xml:epp:iis-1.2“

It is not guaranteed that the EPP server will use the same prefixes in its answers.

The prefixes used by the EPP server can change at any time without notice.

2.3 Rules and Policies

This is a highlight of some of the aspects in the IIS registrar agreement. It is not technical information, but needs to be pointed out to all that are using the .se EPP server.

According to the IIS registrar agreement section 9.1, the registrar shall request the following information from the domain owner:

- Full company name and contact person or if a private individual, their first and last name
- Corporate identity number/personal identification number
- VAT registration number (only for foreign legal entities within the EU)
- Address
- City

- Postal code
- Telephone number
- E-mail address

The registrar shall not undertake any registration services until the domain owner has provided this information.

2.4 Server Usage

The use of the .se EPP server is restricted as follows:

- Connections can be made from four IP addresses which must be submitted through the registrar web.
- Only four connections per registrar, if a fifth connection is opened the oldest connection is closed automatically.
- Max 180 commands per minute. The check is performed on a rolling 60 second basis. If more than 180 commands per minute are detected the server will slow all connections for the client until the requirement is fulfilled.
- All commands are counted toward the 180 commands limit. Every command is counted as one command except the check command.
- The check command counts as so many commands as the number of checks that are contained in the command. Five commands checking one domain count as much as one command checking five domains. Same goes for hosts and contacts.
- Max session time is one hour.
- Idle time is 10 minutes.
- On the test servers XML validation is performed and non validating commands are rejected. This is not done on the production servers. Production servers will try to execute commands to their best ability.

2.5 Client Certificate

The EPP server does require SSL connections with client certificates. You need to upload a valid client certificate through the registrar web to be able to connect to the EPP-server.

2.6 Data format

<clTRID>	Max 63 characters (ASCII)
----------	---------------------------

2.7 RFC 5910 DNSSEC Extension

The server follows RFC5910 section 2 “Migration from RFC 4310”. Therefore the server specifies both extensions in the <greeting/> message and allows clients to specify both as <extURI/> in the <login/> command.

2.8 .SE EPP Test platform

IIS is providing a .se EPP test platform where any registrar can test the EPP system. The test environment provides a safe ‘sandbox’ for registrars to test their system without affecting data on the ‘live’ registry system.

The test database is not linked with the live system in any way and no data is provided. All data in the system has to be generated by registrars themselves.

It is important to note that data, like host that exists in the live system is not in the test system and if you want to use hosts for name servers in domain you have to create them.

There is a web interface provided with the test system where registrars can simulate things like domain deactivations to generate all messages.

2.9 Changes in Rules and Policies

Changes to rules and policies will be informed well in advance to registrars, and if there are changes to the .se EPP protocol, IIS will put up information about the changes 6 months in advance, and will update the testplatform as soon as possible.

This gives every registrar possibility to test the new system, and so make sure that the epp client can work with the new protocol.

We do recommend that you start the test procedure early, to avoid last minute problems.

2.10 EPP Support

IIS is not providing any support for EPP clients.

3 Response

If not stated otherwise all commands will be answered with a response following RFC 5730.

Example:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <response>
    <resData>
      ...
    </resData>
    <result code="1000">
      <msg>Command completed successfully</msg>
    </result>
    <msgQ count="6" id="21"/>
    <trID>
      <clTRID>ABC-12345</clTRID>
      <svTRID>5431</svTRID>
    </trID>
  </response>
</epp>
```

Note that the response MIGHT contain a msgQ element if there are messages queued.

4 Session Commands

4.1 Hello and Greeting

<hello/> and <greeting/> follow RFC 5730.

As indicated in RFC 5730 <hello/> can be used as a keep alive message at any time during a connection.

Example <hello/>:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <hello/>
</epp>
```

Example <greeting/>:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <greeting>
    <svID>epp.iis.se</svID>
    <svDate>2000-06-08T22:00:00.0Z</svDate>
    <svcMenu>
      <version>1.0</version>
      <lang>en</lang>
      <objURI>urn:ietf:params:xml:ns:domain-1.0</objURI>
      <objURI>urn:ietf:params:xml:ns:contact-1.0</objURI>
      <objURI>urn:ietf:params:xml:ns:host-1.0</objURI>
      <svcExtension>
        <extURI>urn:ietf:params:xml:ns:secDNS-1.0</extURI>
        <extURI>urn:ietf:params:xml:ns:secDNS-1.1</extURI>
        <extURI>urn:se:iis:xml:epp:iis-1.2</extURI>
      </svcExtension>
    </svcMenu>
    <dcp>
      <access><all/></access>
      <statement>
        <purpose><prov/></purpose>
        <recipient><ours/><public/></recipient>
        <retention><stated/></retention>
      </statement>
    </dcp>
  </greeting>
</epp>
```

4.2 Login

This command is used to start a session on the server, before you have logged in you can only use <hello/> and <login/>.

<newPW/> is not supported.

<objURI/> is optional, but at least one of domain, host or contact object uri following RFC 5731, 5732, 5733 must be given.

<extURI/> is optional but without iis there is not much you can do. For DNSSec none, one or both namespaces following RFC 4310 and RFC 5910 can be given. See RFC 5910 section 2 for details.

Example <login/> command:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <command>
    <login>
      <clID>ClientX</clID>
      <pw>foo-BAR2</pw>
      <options>
        <version>1.0</version>
        <lang>en</lang>
      </options>
      <svcs>
        <objURI>urn:ietf:params:xml:ns:domain-1.0</objURI>
        <objURI>urn:ietf:params:xml:ns:contact-1.0</objURI>
        <objURI>urn:ietf:params:xml:ns:host-1.0</objURI>
        <svcExtension>
          <extURI>urn:ietf:params:xml:ns:secDNS-1.0</extURI>
          <extURI>urn:ietf:params:xml:ns:secDNS-1.1</extURI>
          <extURI>urn:ietf:params:xml:ns:iis-1.2</extURI>
        </svcExtension>
      </svcs>
    </login>
    <clTRID>ABC-12345</clTRID>
  </command>
</epp>
```

Example response:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <response>
    <result code="1000">
      <msg>Command completed successfully</msg>
    </result>
    <trID>
      <clTRID>ABC-12345</clTRID>
      <svTRID>54321-XYZ</svTRID>
    </trID>
  </response>
</epp>
```

4.3 Logout

This command is used to log out from the session and disconnect from the server.

Implementation follows RFC 5730.

Example <logout/> command:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <command>
    <logout/>
    <clTRID>ABC-12345</clTRID>
  </command>
</epp>
```

Example response:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <response>
    <result code="1500">
      <msg>Command completed successfully; ending session</msg>
    </result>
    <trID>
      <clTRID>ABC-12345</clTRID>
      <svTRID>54321-XYZ</svTRID>
    </trID>
  </response>
</epp>
```

5 Message commands

5.1 Poll

For all changes to a domain, contact or host object initiated by the registry, a message is queued for the sponsoring client to fetch. All registrars are expected to fetch and acknowledge messages regularly using the poll command.

The EPP standard has no definition of messages without an initiating request by the registrar. In that case no clTRID can be supplied and therefore the registrar doesn't know what kind of action has been taken. We have added four tags with the purpose to let the receiver of a message know what kind of action lead to the notification.

<createNotify/>	sent when a host, contact or domain has been created, contains infData for the created object
<updateNotify/>	sent when a host, contact or domain has been updated, contains infData for the updated object
<deleteNotify/>	sent when a host, contact or domain has been deleted, contains host:delete, domain:delete or contact:delete.
<transferNotify/>	sent to the former registrar when a domain has been transferred, contains trnData for a domain or host

Example <poll/> command:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <command>
    <poll op="req" />
    <clTRID>ABC-12345</clTRID>
  </command>
</epp>
```

Example response

```
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <response>
    <result code="1301">
      <msg>Command completed successfully; ack to dequeue</msg>
    </result>
    <msgQ count="60" id="1">
      <qDate>2008-10-07T10:49:36</qDate>
      <msg lang="en"> </msg>
    </msgQ>
    <resData>
      <iis:updateNotify xmlns:iis="urn:se:iis:xml:epp:iis-1.2"
        xsi:schemaLocation="urn:se:iis:xml:epp:iis-1.2 iis-1.2.xsd">
        <domain:infData
          xmlns:domain="urn:ietf:params:xml:ns:domain-1.0"
          xsi:schemaLocation="urn:ietf:params:xml:ns:domain-1.0
            domain-1.0.xsd">
          <domain:name>example.se</domain:name>
          <domain:roid>DOMAIN-1234</domain:roid>
          <domain:status s="ok"/>
          <domain:registrar>abcdef0705-00001</domain:registrar>
          <domain:contact type="admin">abcdef0705-00002</domain:contact>
          <domain:contact type="tech">abcdef0705-00003</domain:contact>
          <domain:ns>
            <domain:hostObj>ns1.example1.se</domain:hostObj>
            <domain:hostObj>ns1.example2.se</domain:hostObj>
          </domain:ns>
          <domain:host>ns.example.se</domain:host>
          <domain:host>ns1.example.se</domain:host>
          <domain:clID>ClientX</domain:clID>
          <domain:crID>ClientY</domain:crID>
          <domain:crDate>1999-04-03T22:00:00.0Z</domain:crDate>
          <domain:upID>ClientX</domain:upID>
          <domain:upDate>1999-12-03T09:00:00.0Z</domain:upDate>
          <domain:exDate>2005-04-03T22:00:00.0Z</domain:exDate>
          <domain:trDate>2000-04-08T09:00:00.0Z</domain:trDate>
        </domain:infData>
      </iis:updateNotify>
    </resData>
    <extension>
      <secDNS:infData
        xmlns:secDNS="urn:ietf:params:xml:ns:secDNS-1.1"
        xsi:schemaLocation="urn:ietf:params:xml:ns:secDNS-1.1
          secDNS-1.1.xsd">
        <secDNS:dsData>
          <secDNS:keyTag>12345</secDNS:keyTag>
          <secDNS:alg>3</secDNS:alg>
          <secDNS:digestType>1</secDNS:digestType>
          <secDNS:digest>49FD46E6C4B45C55D4AC</secDNS:digest>
        </secDNS:dsData>
      </secDNS:infData>
      <iis:infData xmlns:iis="urn:se:iis:xml:epp:iis-1.2"
        xsi:schemaLocation="urn:se:iis:xml:epp:iis-1.2 iis-1.2.xsd">
        <iis:deactDate>2000-11-01</iis:deactDate>
        <iis:delDate>2000-11-11</iis:delDate>
        <iis:clientDelete>0</iis:clientDelete>
      </iis:infData>
    </extension>
    <trID>
      <clTRID>ABC-12345</clTRID>
      <svTRID>5432</svTRID>
    </trID>
  </response>
</epp>
```

Example acknowledgement command:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <command>
    <poll msgID="12345" op="ack" />
    <clTRID>ABC-12345</clTRID>
  </command>
</epp>
```

Example acknowledgement response:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <response>
    <result code="1000">
      <msg>Command completed successfully</msg>
    </result>
    <msgQ count="4" id="12346"/>
    <trID>
      <clTRID>ABC-12345</clTRID>
      <svTRID>7433</svTRID>
    </trID>
  </response>
</epp>
```

Example response to note an empty message queue:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <response>
    <result code="1300">
      <msg>Command completed successfully; no messages</msg>
    </result>
    <trID>
      <clTRID>ABC-12345</clTRID>
      <svTRID>7433</svTRID>
    </trID>
  </response>
</epp>
```


6 Domain Objects

Domain objects contain all data necessary to represent an internet domain name.

6.1 Domain Rules and Policies

- Max ten name servers per domain name, at least two name servers not on the same AS are recommended.
- Max five admin contacts per domain name but stating an admin contact is optional.
- Max five tech contacts per domain name but stating a tech contact is optional.
- Max one billing contact per domain name but stating a billing contact is optional.

Tagname/attribute	
<domain:name/>	1-63 characters a-z,0-9,-. IDN domains in punycode – RFC 3492
<domain:period/>	1 to 10 years or 12 to 120 months are allowed
<domain:ns/>	Only <domain:hostObj/> is supported. A maximum of 10 hosts can be associated to a domain at any given time.
<domain:hostObj/>	Max 255 characters, a-z,0-9,-
<domain:pw/>	Minimum 9 characters, one of a-z, one of A-Z, one of 0-9 and at least one character not in a-z,A-Z,0-9.
<domain:status/>	Only clientHold is supported. If clientHold is set the domain will no longer be accessible through DNS.
<iis:clientDelete/>	To cancel a domain before expiration (update command) 1 = cancel domain 0 = do not cancel domain show if domain has been cancelled (info command) 1 = cancelled 0 = not cancelled
<domain:curExpDate/>	Only the date in format yyyy-mm-dd is allowed Time zone cannot be specified
<iis:ns/>	Extension for the domain:transfer command. Should contain a list of name server as <iis:hostObj/>. This list will replace the current list of name servers. Additionally all DS records will be removed from the domain.

6.2 DNSSEC

- More than one DS record for a domain name is okay
- Maximum are six DS record per domain
- Any algorithm number from 1 to 254 is ok
- Any digest type from 1 to 255 is ok

DNSSEC-keys at IIS: We strongly advise not to use RSA-MD5 as DNSKEY.

6.3 Valid Domain Name characters

.se support domain names in idn or in latin.

Valid Domain Name characters that .se supports is:

Unicode	Character	UTF 8	Name of letter	Comb
U+002d	-	2d	Minus	All
U+0030 - U+0039	0-9	30 – 39	Numbers	All
U+0061 - U+007a	a-z	61 – 7a	Lowercase letters	A
U+00E1	á	c3 a1	a with acute	A
U+00E0	à	c3 a0	a with grave	A
U+01CE	ă	c7 8e	a with caron	A
U+00E2	â	c3 a2	a with circumflex	A
U+00E5	ã	c3 a5	a with ring above	A
U+00E4	ä	c3 a4	a with diaeresis	A
U+00E6	æ	c3 a6	ligature ae	A
U+0107	ć	c4 87	c with acute	A
U+010D	č	c4 8d	c with caron	A
U+00E7	ç	c3 a7	c with cedilla	A
U+0111	đ	c4 91	d with stroke	A
U+00F0	ð	c3 b0	Eth	A
U+00E9	é	c3 a9	e with acute	A
U+00E8	è	c3 a8	e with grave	A
U+00EA	ê	c3 aa	e with circumflex	A
U+011B	ë	c4 9b	e with caron	A
U+00EB	ë	c3 ab	e with diaeresis	A
U+0259	ə	c9 99	schwa	A
U+01E7	ğ	c7 a7	g with caron	A
U+01E5	g	c7 a5	g with stroke	A
U+00ED	í	c3 ad	i with acute	A
U+00EC	ì	c3 ac	i with grave	A
U+00EE	î	c3 ae	i with circumflex	A
U+01D0	ĩ	c7 90	i with caron	A
U+00EF	ï	c3 af	i with diaeresis	A
U+01E9	ķ	c7 a9	k with caron	A
U+0142	ł	c5 82	l with stroke	A
U+0144	ń	c5 88	n with acute	A
U+00F1	ñ	c3 b1	n with tilde	A
U+014B	ŋ	c5 8b	eng	A
U+00F3	ó	c3 b3	o with acute	A
U+00F2	ò	c3 b2	o with grave	A
U+00F4	ô	c3 b4	o with circumflex	A
U+01D2	õ	c7 92	o with caron	A
U+00F5	õ	c3 b5	o with tilde	A
U+00F6	ö	c3 b6	o with diaeresis	A
U+00F8	ø	c3 b8	o with stroke	A
U+0159	ř	c5 99	r with caron	A
U+015B	ś	c5 9b	s with acute	A
U+0161	š	c5 a1	s with caron	A
U+0163	ţ	c5 a3	t with cedilla	A
U+0167	ţ	c5 a7	t with stroke	A
U+00FA	ú	c3 ba	u with acute	A
U+00F9	ù	c3 b9	u with grave	A
U+01D4	ů	c7 94	u with caron	A
U+00FC	ü	c3 bc	u with diaeresis	A
U+00FD	ý	c3 bd	y with acute	A

Unicode	Character	UTF 8	Name of letter	Comb
U+017A	ž	c5 ba	z with acute	A
U+017E	ž	c5 b5	z with caron	A
U+00FE	þ	c3 be	Thorn	A
U+0292	Ʒ	ca 92	Ezh	A
U+01EF	ž	c7 af	ezh with caron	A
U+05D0	א	d7 90	Hebrew letter ALEF	B
U+05D0 + U+05B7	א	d7 90 + d6 b7	Hebrew letter ALEF + Hebrew point PATAH	B
U+05D0 + U+05B8	א	d7 90 + d6 b8	Hebrew letter ALEF + Hebrew point QAMATS	B
U+05D1	ב	d7 91	Hebrew letter BET	B
U+05D1 + U+05BF	ב	d7 91 + d6 bf	Hebrew letter BET + Hebrew point RAFE	B
U+05D2	ג	d7 92	Hebrew letter GIMEL	B
U+05D3	ד	d7 93	Hebrew letter DALET	B
U+05D4	ה	d7 94	Hebrew letter HE	B
U+05D5	ו	d7 95	Hebrew letter VAV	B
U+05D5 + U+05BC	ו	d7 95 + d6 bc	Hebrew letter VAV + Hebrew point DAGESH or MAPIQ	B
U+05D6	ז	d7 96	Hebrew letter ZAYIN	B
U+05D7	ח	d7 97	Hebrew letter HET	B
U+05D8	ט	d7 98	Hebrew letter TET	B
U+05D9	י	d7 99	Hebrew letter YOD	B
U+05D9 + U+05B4	י	d7 99 + d6 b4	Hebrew letter YOD + Hebrew point HIRIQ	B
U+05F2 + U+05B7	ײ	d7 b2 + d6 b7	Hebrew ligature Yiddish double YOD + Hebrew point PATAH	B
U+05DB + +05BC	כּ	d7 9b + d6 bc	Hebrew letter KAF + Hebrew point DAGESH or MAPIQ	B
U+05DB	כ	d7 9b	Hebrew letter KAF	B
U+05DA	ך	d7 9a	Hebrew letter Final KAF	B
U+05DC	ל	d7 9c	Hebrew letter LAMED	B
U+05DE	מ	d7 9e	Hebrew letter MEM	B
U+05DD	ם	d7 9d	Hebrew letter Final MEM	B
U+05E0	נ	d7 a0	Hebrew letter NUN	B
U+05DF	ן	d7 9f	Hebrew letter Final NUN	B
U+05E1	ס	d7 a1	Hebrew letter SAMEKH	B
U+05E2	ע	d7 a2	Hebrew letter AYIN	B
U+05E4 + U+05BC	פּ	d7 a4 + d6 bc	Hebrew letter PE + Hebrew point DAGESH OR MAPIQ	B
U+05E4 + U+05BF	פ	d7 a4 + d6 bf	Hebrew letter PE + Hebrew point RAFE	B
U+05E4	פ	d7 a4	Hebrew letter PE	B
U+05E3	ף	d7 a3	Hebrew letter Final PE	B
U+05E6	צ	d7 a6	Hebrew letter TSADI	B
U+05E5	ץ	d7 a5	Hebrew letter Final TSADI	B
U+05E7	ק	d7 a7	Hebrew letter QOF	B
U+05E8	ר	d7 a8	Hebrew letter RESH	B
U+05E9	ש	d7 a9	Hebrew letter SHIN	B
U+05E9 + U+05C2	שׁ	d7 a9 + d7 82	Hebrew letter SHIN + Hebrew point SIN DOT	B
U+05EA + U+05BC	תּ	d7 aa + d7 bc	Hebrew letter TAV + Hebrew point DAGESH OR MAPIQ	B
U+05EA	ת	d7 aa	Hebrew letter TAV	B

You can not mix characters between latin characters (A) and Hebrew characters (B). A domain name with Hebrew characters can contain any of the above Hebrew characters (B) as well as minus and digits 0 to 9. Domain names with Latin characters can contain any of the above Latin characters (A) as well as minus and digits 0 to 9.

6.4 Check

Follows RFC 5730 and RFC 5731.

Example <check/> command:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <command>
    <check>
      <domain:check xmlns:domain="urn:ietf:params:xml:ns:domain-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:domain-1.0
          domain-1.0.xsd">
        <domain:name>example.se</domain:name>
        <domain:name>example2.se</domain:name>
      </domain:check>
    </check>
    <clTRID>ABC-12345</clTRID>
  </command>
</epp>
```

Example response:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <response>
    <result code="1000">
      <msg>Command completed successfully</msg>
    </result>
    <resData>
      <domain:chkData xmlns:domain="urn:ietf:params:xml:ns:domain-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:domain-1.0
          domain-1.0.xsd">
        <domain:cd>
          <domain:name avail="1">example.se</domain:name>
        </domain:cd>
        <domain:cd>
          <domain:name avail="0">example2.se</domain:name>
          <domain:reason>In use</domain:reason>
        </domain:cd>
      </domain:chkData>
    </resData>
    <trID>
      <clTRID>ABC-12345</clTRID>
      <svTRID>5431</svTRID>
    </trID>
  </response>
</epp>
```

6.5 Info

Follows RFC 5730 and RFC 5731 and RFC 4310 with the following exceptions:

<domain:authInfo/> is not supported, there are no access restrictions

<domain:authInfo/> will not be returned in <domain:infData/>. For security reasons the registry will only save a hash of the authInfo password and is therefore unable to return the data.

<domain:roid/> follows RFC5730 with a format like this DOMAIN_0000000000-SE.

Extensions

<iis:infData/> will be returned in <extension/>. It can contain:

- <iis:clientDelete/> - the clientDelete state of the domain
- <iis:deactDate/> - the date when the domain will be deactivated
- <iis:delDate/> - the date when the domain will be deleted

<iis:relDate/> - the date when the domain will be released
<iis:state/> - the whois state of the domain

<iis:state/> and <iis:clientDelete/> will always be given, the other fields are optional and will be returned only if set.

Example <info/> command:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <command>
    <info>
      <domain:info
        xmlns:domain="urn:ietf:params:xml:ns:domain-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:domain-1.0
          domain-1.0.xsd">
        <domain:name hosts="all">example.se</domain:name>
      </domain:info>
    </info>
    <clTRID>ABC-12345</clTRID>
  </command>
</epp>
```

Example response:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <response>
    <result code="1000">
      <msg>Command completed successfully</msg>
    </result>
    <resData>
      <domain:infData
        xmlns:domain="urn:ietf:params:xml:ns:domain-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:domain-1.0
          domain-1.0.xsd">
        <domain:name>example.se</domain:name>
        <domain:roid>DOMAIN_0000000000-SE</domain:roid>
        <domain:status s="ok"/>
        <domain:registrar>abcdef0705-00001</domain:registrar>
        <domain:contact type="admin">abcdef0705-00002</domain:contact>
        <domain:contact type="tech">abcdef0705-00003</domain:contact>
        <domain:ns>
          <domain:hostObj>ns1.example1.se</domain:hostObj>
          <domain:hostObj>ns1.example2.se</domain:hostObj>
        </domain:ns>
        <domain:host>ns.example.se</domain:host>
        <domain:host>ns1.example.se</domain:host>
        <domain:clID>ClientX</domain:clID>
        <domain:crID>ClientY</domain:crID>
        <domain:crDate>1999-04-03T22:00:00.0Z</domain:crDate>
        <domain:upID>ClientX</domain:upID>
        <domain:upDate>1999-12-03T00:00:00.0Z</domain:upDate>
        <domain:exDate>2005-04-03T00:00:00.0Z</domain:exDate>
        <domain:trDate>2000-04-08T00:00:00.0Z</domain:trDate>
      </domain:infData>
    </resData>
    <extension>
      <sec:infData
        xmlns:sec="urn:ietf:params:xml:ns:secDNS-1.1"
        xsi:schemaLocation="urn:ietf:params:xml:ns:secDNS-1.1
          secDNS-1.1.xsd">
        <sec:dsData>
          <sec:keyTag>12345</sec:keyTag>
          <sec:alg>3</sec:alg>
          <sec:digestType>1</sec:digestType>
          <sec:digest>49FD46E6C4B45C55D4AC</sec:digest>
        </sec:dsData>
      </sec:infData>
      <iis:infData xmlns:iis="urn:se:iis:xml:epp:iis-1.2"
        xsi:schemaLocation="urn:se:iis:xml:epp:iis-1.2 iis-1.2.xsd">
        <iis:deactDate>2000-11-01</iis:deactDate>
      </iis:infData>
    </extension>
  </response>
</epp>
```

```
<iis:delDate>2000-11-11</iis:delDate>
<iis:state>expired</iis:state>
<iis:clientDelete>0</iis:clientDelete>
</iis:infData>
</extension>
<trID>
  <clTRID>ABC-12345</clTRID>
  <svTRID>5432</svTRID>
</trID>
</response>
</epp>
```

6.6 Transfer

Follows RFC 5730 and RFC 5731 with the following exceptions:

Only op="request" is supported. All transfers are rejected or executed immediately, therefore "query", "approve", "reject" are not supported

<domain:pw/> attribute roid is not supported. The password (authorization code) of the domain must be given.

<domain:period/> is not supported. Transfer does not renew domain.

A transfer of a domain does clear <iis:clientDelete/>.

Additionally we have added the possibility to submit new host objects with a transfer request. When new name servers are submitted in the transfer command, the old name servers will be replaced with the new list and all DNSsec DS records will be removed from the domain.

Example <transfer/> request command:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <command>
    <transfer op="request">
      <domain:transfer
        xmlns:domain="urn:ietf:params:xml:ns:domain-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:domain-1.0
          domain-1.0.xsd">
        <domain:name>example.se</domain:name>
        <domain:authInfo>
          <domain:pw>2fooBAR-barFOO</domain:pw>
        </domain:authInfo>
        </domain:transfer>
      </transfer>
      <extension>
        <iis:transfer xmlns:iis="urn:se:iis:xml:epp:iis-1.2"
          xsi:schemaLocation="urn:se:iis:xml:epp:iis-1.2 iis-1.2.xsd">
          <iis:ns>
            <iis:hostObj>ns.exempel.se</iis:hostObj>
          </iis:ns>
          </iis:transfer>
        </extension>
        <clTRID>ABC-12345</clTRID>
      </command>
    </epp>
```

Example <transfer/> request response:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <response>
    <result code="1000">
      <msg>Command completed successfully</msg>
    </result>
    <resData>
      <domain:trnData
        xmlns:domain="urn:ietf:params:xml:ns:domain-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:domain-1.0
          domain-1.0.xsd">
        <domain:name>example.se</domain:name>
        <domain:trStatus>serverApproved</domain:trStatus>
        <domain:reID>ClientX</domain:reID>
        <domain:reDate>2000-06-08T22:00:00.0Z</domain:reDate>
        <domain:acID>ClientX</domain:acID>
        <domain:acDate>2000-06-08T22:00:00.0Z</domain:acDate>
      </domain:trnData>
    </resData>
    <trID>
      <clTRID>ABC-12345</clTRID>
      <svTRID>54322-XYZ</svTRID>
    </trID>
  </response>
</epp>
```

6.7 Create

Follows RFC 5730, RFC 5731 and RFC 4310.

<domain:period/> can be any value between 12 and 120 months. Additionally values of 1 to 10 years are supported.

Example <create/> command:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <command>
    <create>
```

```
<domain:create
  xmlns:domain="urn:ietf:params:xml:ns:domain-1.0"
  xsi:schemaLocation="urn:ietf:params:xml:ns:domain-1.0
  domain-1.0.xsd">
  <domain:name>example.se</domain:name>
  <domain:period unit="y">5</domain:period>
  <domain:ns>
    <domain:hostObj>ns1.example1.se</domain:hostObj>
    <domain:hostObj>ns2.example2.se</domain:hostObj>
  </domain:ns>
  <domain:registrar>jd-1234</domain:registrar>
  <domain:contact type="admin">sh-8013</domain:contact>
  <domain:contact type="tech">sh-8013</domain:contact>
  <domain:authInfo>
    <domain:pw>2fooBAR3+</domain:pw>
  </domain:authInfo>
</domain:create>
</create>
<extension>
  <secDNS:create
    xmlns:secDNS="urn:ietf:params:xml:ns:secDNS-1.0"
    xsi:schemaLocation="urn:ietf:params:xml:ns:secDNS-1.0
    secDNS-1.0.xsd">
    <secDNS:dsData>
      <secDNS:keyTag>12345</secDNS:keyTag>
      <secDNS:alg>3</secDNS:alg>
      <secDNS:digestType>1</secDNS:digestType>
      <secDNS:digest>49FD46E6C4B45C55D4AC</secDNS:digest>
    </secDNS:dsData>
  </secDNS:create>
</extension>
<clTRID>ABC-12345</clTRID>
</command>
</epp>
```

Example response:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0
  epp-1.0.xsd">
  <response>
    <result code="1000">
      <msg>Command completed successfully</msg>
    </result>
    <resData>
      <domain:creData
        xmlns:domain="urn:ietf:params:xml:ns:domain-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:domain-1.0
        domain-1.0.xsd">
        <domain:name>example.se</domain:name>
        <domain:crDate>2009-09-29T00:00:00.0Z</domain:crDate>
        <domain:exDate>2014-09-29T00:00:00.0Z</domain:exDate>
      </domain:creData>
    </resData>
    <trID>
      <clTRID>ABC-12345</clTRID>
      <svTRID>54321-XYZ</svTRID>
    </trID>
  </response>
</epp>
```

6.8 Delete

The delete command is supported. The clientDelete flag will be set, which means that the domain will be deactivated for 60 days and then deleted. See also chapter 6.9 for the <iis:clientDelete/> extension.

6.9 Update

Follows RFC 5730, RFC 5731 and RFC 4310. The following extensions have been added:

<secDNS:keyTag/> - When DNSSEC extensions according to RFC 4310 are used, keyTag "0" will remove all DS posts.

<iis:clientDelete/> - Cancel a domain (1 = cancel, 0 = remove cancel). This flag is automatically set to zero if the domain is transferred. If the domain is cancelled it will be deactivated for 60 days and then deleted. A PendingDelete status will also be applied to the domain as well as ServerHold.

Example <update/> command:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <command>
    <update>
      <domain:update
        xmlns:domain="urn:ietf:params:xml:ns:domain-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:domain-1.0
          domain-1.0.xsd">
        <domain:name>example.se</domain:name>
        <domain:add>
          <domain:ns>
            <domain:hostObj>ns2.example2.se</domain:hostObj>
          </domain:ns>
          <domain:contact type="tech">mak-21</domain:contact>
          <domain:status s="clientHold"
            lang="en">Payment overdue.</domain:status>
        </domain:add>
        <domain:rem>
          <domain:ns>
            <domain:hostObj>ns1.example1.se</domain:hostObj>
          </domain:ns>
          <domain:contact type="tech">sh-8013</domain:contact>
        </domain:rem>
        <domain:chg>
          <domain:registrant>sh-8013</domain:registrant>
          <domain:authInfo>
            <domain:pw>2BARfoo%=</domain:pw>
          </domain:authInfo>
        </domain:chg>
        </domain:update>
      </update>
      <extension>
        <secDNS:update
          xmlns:secDNS="urn:ietf:params:xml:ns:secDNS-1.0"
          xsi:schemaLocation="urn:ietf:params:xml:ns:secDNS-1.0
            secDNS-1.0.xsd">
          <secDNS:add>
            <secDNS:dsData>
              <secDNS:keyTag>12345</secDNS:keyTag>
              <secDNS:alg>3</secDNS:alg>
              <secDNS:digestType>1</secDNS:digestType>
              <secDNS:digest>49FD46E6C4B45C55D4AC</secDNS:digest>
            </secDNS:dsData>
          </secDNS:add>
        </secDNS:update>
        <iis:update
          xmlns:iis="urn:se:iis:xml:epp:iis-1.2"
          xsi:schemaLocation="urn:se:iis:xml:epp:iis-1.2 iis-1.2.xsd">
          <iis:clientDelete>0</iis:clientDelete>
        </iis:update>
      </extension>
      <clTRID>ABC-12345</clTRID>
    </command>
  </epp>
```

Example response:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <response>
    <result code="1000">
      <msg>Command completed successfully</msg>
    </result>
  </response>
</epp>
```

```
<trID>
  <clTRID>ABC-12345</clTRID>
  <svTRID>54321-XYZ</svTRID>
</trID>
</response>
</epp>
```

6.10 Renew

Follows RFC 5730, RFC 5731.

<domain:period/> can be any value between 12 and 120 months. Additionally values of 1 to 10 years are supported.

A domain can be renewed at any time. However, expiry date (year) can be max 10 years away from when the renewal takes place. Renew is possible until one day before <iis:delDate/>.

Example <renew/> command:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <command>
    <renew>
      <domain:renew
        xmlns:domain="urn:ietf:params:xml:ns:domain-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:domain-1.0
          domain-1.0.xsd">
        <domain:name>exempel.se</domain:name>
        <domain:curExpDate>2008-11-05</domain:curExpDate>
        <domain:period unit="m">17</domain:period>
      </domain:renew>
    </renew>
    <clTRID>myTRID-1</clTRID>
  </command>
</epp>
```

Example response:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd"
  xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance">
  <response>
    <resData>
      <domain:renData
        xsi:schemaLocation="urn:ietf:params:xml:ns:domain-1.0
          domain-1.0.xsd"
        xmlns:domain="urn:ietf:params:xml:ns:domain-1.0">
        <domain:name>example.se</domain:name>
        <domain:exDate>2010-04-05T00:00:00Z</domain:exDate>
      </domain:renData>
    </resData>
    <result code="1000">
      <msg>Command completed successfully</msg>
    </result>
    <trID>
      <clTRID>myTRID-1</clTRID>
      <svTRID>40</svTRID>
    </trID>
  </response>
</epp>
```

7 Contact Objects

Follows RFC 5730, RFC 5733. The following extensions are added:

<iis:orgno/> - personal or organisational number

<iis:vatno/> - VAT number

7.1 Contact Rules and Policies

7.1.1 <CONTACT:NAME/>

This is required information. In this field the name of the contact person must be stated, but if the field <contact:org> is completed, it may be a department or function. If the field <contact:org/> is not completed the contact will be registered as a private person. In that case the, this field **MUST BE** completed with the holder's first and last name.

7.1.2 <CONTACT:ORG/>

This is required information if the created contact is a legal person. If specified the contact is assumed to be a company. The field must contain the registered company name.

7.1.3 <CONTACT:STREET/>

This is required information if the contact has a PO Box or street address, otherwise optional. Max three tags can be given.

7.1.4 <CONTACT:CITY/>

This is required information. The field must contain information about which city the contact has their domicile.

7.1.5 <CONTACT:EMAIL/>

This is required information. Must be a valid email address which is connected to the holder of the contact.

7.1.6 <CONTACT:PC/>

Postal code is required information. For Swedish addresses it must be exactly five digits 0-9 (no spaces). Otherwise 1 to 16 characters a-z, A-Z, 0-9, “,”, “-” and space with at least one character other than space.

7.1.7 <CONTACT:CC/>

Country code is required information at it must be an ISO 3166 Alpha-2 country code.

7.1.8 <CONTACT:VOICE/>

Telephone number is required information. Telephone numbers should be given in E.164. Plus sign, ITU country code, dot, 1 to 14 digits, for example +46.84523500.

Extension must be given, but can be empty or 1 to 40 digits 0-9

7.1.9 <CONTACT:DISCLOSE/>

If <contact:org/> is set protection from disclosure is not possible. If regarded as a Swedish sole proprietorship the contact is however protected from disclosure.

7.1.10 <IIS:ORGNO/>

A valid personal- or organizational number is required for all contacts, or one who can be identified through proof of registration in a record maintained by a public authority or by an organization with functions comparable to that of a public authority.

Starts with ISO 3166 Alpha-2 country code in square brackets. If the country code for Sweden is given [SE] a valid Swedish personal or organizational number is to be given (6 digits, dash, 4 digits). For example

[SE]802405-0190.

7.1.11 <CONTACT:AUTHINFO>

Contact:Authinfo is not supported for create and update. It is available for “Contact Info” for non sponsoring clients to get all information for a contact.

```
<contact:authInfo>
```

```
<contact:pw roid="DOMAIN_0000000000-SE">2BARfoo%=</></contact:pw>
```

```
</contact:authInfo>
```

The opportunity to obtain all contact information for a holder via the EPP command “Contact Info” if the registrar has the current authorization code for the domain and domain ROID that the contact has roles in..

Tagname/attribute	Comment
<contact:id/>	Minimum length 3 characters Maximum length is 16 characters Must contains letters a-z,A-Z or digits 0-9 or dash “-“
<contact:postalInfo/>	Every contact object can have 2 addresses, one international (“int”) and one local (“loc”). The international address may only contain us-ascii while the local can contain a collection of other UTF-8 characters. If the local and international <contact:postalInfo/> differ, the local is given precedence. The local address is mandatory.
<contact:name/>	1 to 255 characters. This is required information
<contact:org/>	1 to 255 characters If specified the contact is assumed to be a company..
<contact:addr/>	
<contact:street/>	At least 0 max 3 can be given 1 to 255 characters
<contact:city/>	1 to 128 characters. This is required information.
<contact:sp/>	1 to 128 characters
<contact:pc/>	For Swedish addresses it must be exactly 5 digits 0-9 (no spaces). Otherwise 1 to 16 characters, a-z, A-Z, 0-9, “,”, “-“ and space with at least one character other than space.
<contact:cc/>	ISO 3166 Alpha-2 country codes. Country code is required information.

Tagname/attribute	Comment
<contact:voice/>	Required information. Telephone numbers should be given in E.164. Plus sign, ITU country code, dot, 1 to 14 digits Extension must be given, but can be empty or 1 to 40 digits 0-9.
<contact:fax/>	Optional. For format see <contact:voice/>
<contact:email/>	Must be a valid e-mail address.
<contact:authInfo/>	See 7.1.11
<contact:disclose/>	If <contact:org/> is set protection from disclosure is not possible. The EPP server will not issue an error if protection from disclosure is tried anyway.
<iis:orgno/>	Starts with ISO 3166 Alpha-2 country code in square brackets. If the country code for Sweden is given [SE] a valid Swedish personal or organisational number must be given (6 digits, dash, 4 digits), otherwise 1 to 123 characters can follow. If <contact:org/> is empty and the country code for Sweden [SE] is given <iis:orgno/> must be a personal number not an organisational number.
<iis:vatno/>	Starts with a two letter country code (uppercase), followed by an optional space, followed by a country specific string containing digits 0-9, and letters a-z and A-Z.

7.2 Character sets for postallInfo

Every contact object can have 2 addresses, one international ("int") and one local ("loc"). The international address may only contain us-ascii while the local can contain a collection of other UTF-8 characters.

Both types allows spaces.

7.2.1 INT ADDRESS TYPE ALLOWED CHARACTERS

Unicode	Character	UTF 8	Name
U+0020		20	Space
U+0021	!	21	Exclamation mark
U+0022	"	22	Quotation mark
U+0023	#	23	Number sign
U+0024	\$	24	Dollar sign
U+0025	%	25	Percent sign
U+0026	&	26	Ampersand
U+0027	'	27	Apostrophe
U+0028	(28	Left Parentheses
U+0029)	29	Right Parentheses
U+002a	*	2a	Asterisk
U+002b	+	2b	Plus sign
U+002c	,	2c	Comma
U+002d	-	2d	Minus
U+002e	.	2e	Dot
U+002f	/	2f	Slash
U+0030 - U+0039	0-9	30 – 39	Numbers
U+003a	:	3a	Colon
U+003b	;	3b	Semicolon
U+003c	<	3c	Less-than sign
U+003d	=	3d	Equal sign
U+003e	>	3e	Greater-than sign
U+003f	?	3f	Question mark
U+0040	@	40	At sign
U+0041 - U+005a	A-Z	41 – 5a	Uppercase letters
U+005b	[5b	Left Square brackets
U+005c	\	5c	Backslash
U+005d]	5d	Right Square brackets
U+005e	^	5e	Caret
U+005f	_	5f	Underscore
U+0060	`	60	Grave accent
U+0061 - U+007a	a-z	61 – 7a	Lowercase letters
U+007b	{	7b	Left Bracket
U+007c		7c	Vertical bar
U+007d	}	7d	Right Bracket
U+007e	~	7e	Tilde

7.2.1 LOCAL ADDRESS TYPE ALLOWED CHARACTERS

Int Address type allowed characters plus the following

Unicode	Character	UTF 8	Description
U+00A7	§	c2 a7	Section sign
U+00B4	´	c2 b4	Acute accent
U+00B7	·	c2 b7	Middle dot
U+00C0	À	c3 80	Latin capital letter A with grave
U+00C1	Á	c3 81	Latin capital letter A with acute
U+00C2	Â	c3 82	Latin capital letter A with circumflex
U+00C3	Ã	c3 83	Latin capital letter A with tilde
U+00C4	Ä	c3 84	Latin capital letter A with diaeresis
U+00C5	Å	c3 85	Latin capital letter A with ring above
U+00C6	Æ	c3 86	Latin capital letter AE
U+00C7	Ç	c3 87	Latin capital letter C with cedilla
U+00C8	È	c3 88	Latin capital letter E with grave
U+00C9	É	c3 89	Latin capital letter E with acute
U+00CA	Ê	c3 8a	Latin capital letter E with circumflex
U+00CB	Ë	c3 8b	Latin capital letter E with diaeresis
U+00CC	Ì	c3 8c	Latin capital letter I with grave
U+00CD	Í	c3 8d	Latin capital letter I with acute
U+00CE	Î	c3 8e	Latin capital letter I with circumflex
U+00CF	Ï	c3 8f	Latin capital letter I with diaeresis
U+00D0	Ð	c3 90	Latin capital letter ETH
U+00D1	Ñ	c3 91	Latin capital letter N with tilde
U+00D2	Ò	c3 92	Latin capital letter O with grave
U+00D3	Ó	c3 93	Latin capital letter O with acute
U+00D4	Ô	c3 94	Latin capital letter O with circumflex
U+00D5	Õ	c3 95	Latin capital letter O with tilde
U+00D6	Ö	c3 96	Latin capital letter O with diaeresis
U+00D8	Ø	c3 98	Latin capital letter O with stroke

Unicode	Character	UTF 8	Description
U+00D9	Û	c3 99	Latin capital letter U with grave
U+00DA	Ū	c3 9a	Latin capital letter U with acute
U+00DB	Ů	c3 9b	Latin capital letter U with circumflex
U+00DC	Ü	c3 9c	Latin capital letter U with diaeresis
U+00DD	Ý	c3 9d	Latin capital letter Y with acute
U+00DE	Þ	c3 9e	Latin capital letter THORN
U+00DF	ß	c3 9f	Latin small letter SHARP S
U+00E0	à	c3 a0	Latin small letter A with grave
U+00E1	á	c3 a1	Latin small letter A with acute
U+00E2	â	c3 a2	Latin small letter A with circumflex
U+00E3	ã	c3 a3	Latin small letter A with tilde
U+00E4	ä	c3 a4	Latin small letter A with diaeresis
U+00E5	å	c3 a5	Latin small letter A with ring above
U+00E6	æ	c3 a6	Latin small letter AE
U+00E7	ç	c3 a7	Latin small letter C with cedilla
U+00E8	è	c3 a8	Latin small letter E with grave
U+00E9	é	c3 a9	Latin small letter E with acute
U+00EA	ê	c3 aa	Latin small letter E with circumflex
U+00EB	ë	c3 ab	Latin small letter E with diaeresis
U+00EC	ì	c3 ac	Latin small letter I with grave
U+00ED	í	c3 ad	Latin small letter I with acute
U+00EE	î	c3 ae	Latin small letter I with circumflex
U+00EF	ï	c3 af	Latin small letter I with diaeresis
U+00F0	ð	c3 b0	Latin small letter ETH
U+00F1	ñ	c3 b1	Latin small letter N with tilde
U+00F2	ò	c3 b2	Latin small letter O with grave
U+00F3	ó	c3 b3	Latin small letter O with acute
U+00F4	ô	c3 b4	Latin small letter O with circumflex
U+00F5	õ	c3 b5	Latin small letter O with tilde
U+00F6	ö	c3 b6	Latin small letter O with diaeresis
U+00F8	ø	c3 b8	Latin small letter O with stroke
U+00F9	ù	c3 b9	Latin small letter U with grave
U+00FA	ú	c3 ba	Latin small letter U with acute
U+00FB	û	c3 bb	Latin small letter U with circumflex
U+00FC	ü	c3 bc	Latin small letter U with diaeresis
U+00FD	ý	c3 bd	Latin small letter Y with acute
U+00FE	þ	c3 be	Latin small letter THORN
U+00FF	ÿ	c3 bf	Latin small letter Y with diaeresis
U+0100	Ā	c4 80	Latin capital letter A with macron
U+0101	ā	c4 81	Latin small letter A with macron
U+0102	Ă	c4 82	Latin capital letter A with breve
U+0103	ă	c4 83	Latin small letter A with breve
U+0104	Ą	c4 84	Latin capital letter A with ogonek
U+0105	ą	c4 85	Latin small letter A with ogonek
U+0106	Ć	c4 86	Latin capital letter C with acute
U+0107	ć	c4 87	Latin small letter C with acute
U+010A	Ĉ	c4 8a	Latin capital letter C with dot above
U+010B	ĉ	c4 8b	Latin small letter C with dot above
U+010C	Č	c4 8c	Latin capital letter C with caron
U+010D	č	c4 8d	Latin small letter C with caron
U+010E	Ď	c4 8e	Latin capital letter D with caron
U+010F	ď	c4 8f	Latin small letter D with caron
U+0110	Đ	c4 90	Latin capital letter D with stroke
U+0111	đ	c4 91	Latin small letter D with stroke
U+0112	Ē	c4 92	Latin capital letter E with macron
U+0113	ē	c4 93	Latin small letter E with macron
U+0116	Ĕ	c4 96	Latin capital letter E with dot above
U+0117	ĕ	c4 97	Latin small letter E with dot above
U+0118	Ę	c4 98	Latin capital letter E with ogonek
U+0119	ę	c4 99	Latin small letter E with ogonek
U+011A	Ě	c4 9a	Latin capital letter E with caron
U+011B	ě	c4 9b	Latin small letter E with caron
U+011E	Ĝ	c4 9e	Latin capital letter G with breve
U+011F	ğ	c4 9f	Latin small letter G with breve
U+0120	Ğ	c4 a0	Latin capital letter G with dot above
U+0121	ġ	c4 a1	Latin small letter G with dot above
U+0122	Ġ	c4 a2	Latin capital letter G with cedilla
U+0123	ġ	c4 a3	Latin small letter G with cedilla
U+0126	Ĥ	c4 a6	Latin capital letter H with stroke
U+0127	ĥ	c4 a7	Latin small letter H with stroke
U+012A	Ī	c4 aa	Latin capital letter I with macron
U+012B	ī	c4 ab	Latin small letter I with macron
U+012E	Į	c4 ae	Latin capital letter I with ogonek

Unicode	Character	UTF 8	Description
U+012F	ı	c4 af	Latin small letter I with ogonek
U+0130	İ	c4 b0	Latin capital letter I with dot above
U+0131	ı	c4 b1	Latin small letter dotless I
U+0136	Ķ	c4 b6	Latin capital letter K with cedilla
U+0137	ķ	c4 b7	Latin small letter K with cedilla
U+0139	Ĺ	c4 b9	Latin capital letter L with acute
U+013A	ĺ	c4 ba	Latin small letter L with acute
U+013B	Ļ	c4 bb	Latin capital letter L with cedilla
U+013C	ļ	c4 bc	Latin small letter L with cedilla
U+013D	Ľ	c4 bd	Latin capital letter L with caron
U+013E	ľ	c4 be	Latin small letter L with caron
U+0141	Ł	c5 81	Latin capital letter L with stroke
U+0142	ł	c5 82	Latin small letter L with stroke
U+0143	Ń	c5 83	Latin capital letter N with acute
U+0144	ń	c5 84	Latin small letter N with acute
U+0145	Ņ	c5 85	Latin capital letter N with cedilla
U+0146	ņ	c5 86	Latin small letter N with cedilla
U+0147	Ň	c5 87	Latin capital letter N with caron
U+0148	ň	c5 88	Latin small letter N with caron
U+014A	Đ	c5 8a	Latin capital letter ENG
U+014B	đ	c5 8b	Latin small letter ENG
U+014C	Ō	c5 8c	Latin capital letter O with macron
U+014D	ō	c5 8d	Latin small letter O with macron
U+0150	Ŏ	c5 90	Latin capital letter O with double acute
U+0151	ŏ	c5 91	Latin small letter O with double acute
U+0152	Œ	c5 92	Latin capital ligature OE
U+0153	œ	c5 93	Latin small ligature OE
U+0154	Ŕ	c5 94	Latin capital letter R with acute
U+0155	ŗ	c5 95	Latin small letter R with acute
U+0156	Ŗ	c5 96	Latin capital letter R with cedilla
U+0157	ŗ	c5 97	Latin small letter R with cedilla
U+0158	Ř	c5 98	Latin capital letter R with caron
U+0159	ř	c5 99	Latin small letter R with caron
U+015A	Ś	c5 9a	Latin capital letter S with acute
U+015B	ś	c5 9b	Latin small letter S with acute
U+015E	Ŝ	c5 9e	Latin capital letter S with cedilla
U+015F	ŝ	c5 9f	Latin small letter S with cedilla
U+0160	Š	c5 a0	Latin capital letter S with caron
U+0161	š	c5 a1	Latin small letter S with caron
U+0162	Ţ	c5 a2	Latin capital letter T with cedilla
U+0163	ţ	c5 a3	Latin small letter T with cedilla
U+0164	Ț	c5 a4	Latin capital letter T with caron
U+0165	ț	c5 a5	Latin small letter T with caron
U+0166	Ț	c5 a6	Latin capital letter T with stroke
U+0167	ț	c5 a7	Latin small letter T with stroke
U+016A	Ū	c5 aa	Latin capital letter U with macron
U+016B	ū	c5 ab	Latin small letter U with macron
U+016E	Ů	c5 ae	Latin capital letter U with ring above
U+016F	ů	c5 af	Latin small letter U with ring above
U+0170	Ű	c5 b0	Latin capital letter U with double acute
U+0171	ű	c5 b1	Latin small letter U with double acute
U+0172	Ų	c5 b2	Latin capital letter U with ogonek
U+0173	ų	c5 b3	Latin small letter U with ogonek
U+0174	Ŵ	c5 b4	Latin capital letter W with circumflex
U+0175	ŵ	c5 b5	Latin small letter W with circumflex
U+0176	Ỳ	c5 b6	Latin capital letter Y with circumflex
U+0177	ỳ	c5 b7	Latin small letter Y with circumflex
U+0178	Ỳ	c5 b8	Latin capital letter Y with diaeresis
U+0179	Ź	c5 b9	Latin capital letter Z with acute
U+017A	ź	c5 ba	Latin small letter Z with acute
U+017B	Ż	c5 bb	Latin capital letter Z with dot above
U+017C	ż	c5 bc	Latin small letter Z with dot above
U+017D	Ž	c5 bd	Latin capital letter Z with caron
U+017E	ž	c5 be	Latin small letter Z with caron
U+018F	Ə	c6 8f	Latin capital letter SCHWA
U+01B7	Ʒ	c6 b7	Latin capital letter EZH
U+01CD	Ā	c7 8d	Latin capital letter A with caron
U+01CE	ā	c7 8e	Latin small letter A with caron
U+01CF	Ī	c7 8f	Latin capital letter I with caron
U+01D0	ī	c7 90	Latin small letter I with caron
U+01D1	Ō	c7 91	Latin capital letter O with caron
U+01D2	ō	c7 92	Latin small letter O with caron

Unicode	Character	UTF 8	Description
U+01D3	Ů	c7 93	Latin capital letter U with caron
U+01D4	ů	c7 94	Latin small letter U with caron
U+01E4	Ġ	c7 a4	Latin capital letter G with stroke
U+01E5	ġ	c7 a5	Latin small letter G with stroke
U+01E6	Ĝ	c7 a6	Latin capital letter G with caron
U+01E7	ĝ	c7 a7	Latin small letter G with caron
U+01E8	Ķ	c7 a8	Latin capital letter K with caron
U+01E9	ķ	c7 a9	Latin small letter K with caron
U+01EE	Ž	c7 ae	Latin capital letter EZH with caron
U+01EF	ž	c7 af	Latin small letter EZH with caron
U+0259	ə	c9 99	Latin small letter SCHWA
U+0292	Ʒ	ca 92	Latin small letter EZH
U+1E80	Ŵ	e1 ba 80	Latin capital letter W with grave
U+1E81	ŵ	e1 ba 81	Latin small letter W with grave
U+1E82	Ŷ	e1 ba 82	Latin capital letter W with acute
U+1E83	ŷ	e1 ba 83	Latin small letter W with acute
U+1E84	Ÿ	e1 ba 84	Latin capital letter W with diaeresis
U+1E85	ÿ	e1 ba 85	Latin small letter W with diaeresis
U+1EF2	Ỳ	e1 bb b2	Latin capital letter Y with grave
U+1EF3	ỳ	e1 bb b3	Latin small letter Y with grave

7.3 Check

Follows RFC 5730 and RFC 5733.

Example <check/> command:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <command>
    <check>
      <contact:check
        xmlns:contact="urn:ietf:params:xml:ns:contact-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:contact-1.0
          contact-1.0.xsd">
        <contact:id>abcdef0705-00001</contact:id>
        <contact:id>bcdefg0705-00001</contact:id>
        <contact:id>abcdef0705-00002</contact:id>
      </contact:check>
    </check>
    <clTRID>ABC-12345</clTRID>
  </command>
</epp>
```

Example response:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <response>
    <result code="1000">
      <msg>Command completed successfully</msg>
    </result>
    <resData>
      <contact:chkData
        xmlns:contact="urn:ietf:params:xml:ns:contact-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:contact-1.0
          contact-1.0.xsd">
        <contact:cd>
          <contact:id avail="1">abcdef0705-00001</contact:id>
        </contact:cd>
        <contact:cd>
          <contact:id avail="0">bcdefg0705-00001</contact:id>
          <contact:reason>In use</contact:reason>
        </contact:cd>
        <contact:cd>
          <contact:id avail="1">abcdef0705-00002</contact:id>
        </contact:cd>
      </contact:chkData>
    </resData>
    <trID>
      <clTRID>ABC-12345</clTRID>
      <svTRID>54322-XYZ</svTRID>
    </trID>
  </response>
</epp>
```

7.4 Info

Follows RFC 5730 and RFC 5733. The response will contain the following extensions:

<iis:orgno/> - personal or organisational number

<iis:vatno/> - VAT number

Only the sponsoring client is allowed to execute this command. Anybody else will receive an error. If the info command contains the current authorization code for the domain and domain ROID all contact information can be obtained even if the registrar is not the sponsoring client. More information about this in chapter 7.1.11.

```
<contact:authInfo>
<contact:roid/> follows RFC5730 with a format like this CONTACT_0000000000-SE.
</contact:authInfo>
```

Example <info/> command:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <command>
    <info>
      <contact:info
        xmlns:contact="urn:ietf:params:xml:ns:contact-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:contact-1.0
          contact-1.0.xsd">
        <contact:id>sh0808-8013</contact:id>
      </contact:info>
    </info>
    <clTRID>ABC-12345</clTRID>
  </command>
</epp>
```

Example response:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <response>
    <result code="1000">
      <msg>Command completed successfully</msg>
    </result>
    <resData>
      <contact:infData
        xmlns:contact="urn:ietf:params:xml:ns:contact-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:contact-1.0
          contact-1.0.xsd">
        <contact:id>sh0808-8013</contact:id>
        <contact:roid>CONTACT_0000000000-SE</contact:roid>
        <contact:status s="ok"/>
        <contact:postalInfo type="loc">
          <contact:name>Example Example</contact:name>
          <contact:org>IIS (The IIS)</contact:org>
          <contact:addr>
            <contact:street>IIS (The IIS)</contact:street>
            <contact:street>Sthmlvägen 100</contact:street>
            <contact:city>Stockholm</contact:city>
            <contact:pc>11111</contact:pc>
            <contact:cc>SE</contact:cc>
          </contact:addr>
        </contact:postalInfo>
        <contact:voice x="">+46.84523500</contact:voice>
        <contact:fax x="">+46.84523502</contact:fax>
        <contact:email>example@example.se</contact:email>
        <contact:clID>ClientY</contact:clID>
        <contact:crID>ClientX</contact:crID>
        <contact:crDate>1999-04-03T22:00:00.0Z</contact:crDate>
        <contact:upID>ClientX</contact:upID>
        <contact:upDate>1999-12-03T09:00:00.0Z</contact:upDate>
        <contact:disclose flag="0">
          <contact:voice/>
          <contact:email/>
        </contact:disclose>
      </contact:infData>
    </resData>
    <extension>
      <iis:infData xmlns:iis="urn:se:iis:xml:epp:iis-1.2"
        xsi:schemaLocation="urn:se:iis:xml:epp:iis-1.2 iis-1.2.xsd">
        <iis:orgno>[SE]802405-0190</iis:orgno>
        <iis:vatno>SE802405019001</iis:vatno>
      </iis:infData>
    </extension>
  </trID>
```

```
<clTRID>ABC-12345</clTRID>
<svTRID>54322-XYZ</svTRID>
</trID>
</response>
</epp>
```

7.5 Transfer

Contacts cannot be transferred.

7.6 Create

Follows RFC 5730 and RFC 5733. The following extensions are supported:

<iis:orgno/> - personal or organisational number

<iis:vatno/> - VAT number

<contact:authInfo/> is not supported.

Example <create/> command:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <command>
    <create>
      <contact:create>
        xmlns:contact="urn:ietf:params:xml:ns:contact-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:contact-1.0
          contact-1.0.xsd">
          <contact:id>abcdef0704-00001</contact:id>
          <contact:postalInfo type="loc">
            <contact:name>Example Example</contact:name>
            <contact:org>IIS (The IIS)</contact:org>
            <contact:addr>
              <contact:street>Sthlmvägen 100</contact:street>
              <contact:street>Sthlmvägen 100</contact:street>
              <contact:city>Stockholm</contact:city>
              <contact:pc>11111</contact:pc>
              <contact:cc>SE</contact:cc>
            </contact:addr>
          </contact:postalInfo>
          <contact:voice x=" "+46.84523500</contact:voice>
          <contact:fax x=" "+46.84523502</contact:fax>
          <contact:email>example@example.se</contact:email>
          <contact:disclose flag="0">
            <contact:voice/>
            <contact:email/>
          </contact:disclose>
        </contact:create>
      </create>
      <extension>
        <iis:create xmlns:iis="urn:se:iis:xml:epp:iis-1.2"
          xsi:schemaLocation="urn:se:iis:xml:epp:iis-1.2 iis-1.2.xsd">
          <iis:orgno>[SE]802405-0190</iis:orgno>
          <iis:vatno>SE802405019001</iis:vatno>
        </iis:create>
      </extension>
    </command>
  </epp>
```

Example response:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <response>
    <result code="1000">
      <msg>Command completed successfully</msg>
    </result>
  </response>
</epp>
```

```
<resData>
  <contact:creData
    xmlns:contact="urn:ietf:params:xml:ns:contact-1.0"
    xsi:schemaLocation="urn:ietf:params:xml:ns:contact-1.0
    contact-1.0.xsd">
    <contact:id>abcdef0704-00001</contact:id>
    <contact:crDate>1999-04-03T22:00:00.0Z</contact:crDate>
  </contact:creData>
</resData>
<trID>
  <clTRID>ABC-12345</clTRID>
  <svTRID>54321-XYZ</svTRID>
</trID>
</response>
</epp>
```

7.7 Delete

Follows RFC 5730 and RFC 5733.

Contacts may not be deleted if they are linked to a domain.

Example <delete/> command:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <command>
    <delete>
      <contact:delete
        xmlns:contact="urn:ietf:params:xml:ns:contact-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:contact-1.0
        contact-1.0.xsd">
        <contact:id>abc0704-00001</contact:id>
      </contact:delete>
    </delete>
    <clTRID>ABC-12345</clTRID>
  </command>
</epp>
```

Example response:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <response>
    <result code="1000">
      <msg>Command completed successfully</msg>
    </result>
    <trID>
      <clTRID>ABC-12345</clTRID>
      <svTRID>54321-XYZ</svTRID>
    </trID>
  </response>
</epp>
```

7.8 Update

Follows RFC 5730 and RFC 5733. The following extension is supported:

<iis:vatno/> - VAT number

Please note that <iis:orgno/> cannot be updated. <contact:authInfo/> and <contact:status/> are not supported.

Example <update/> command:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <command>
```

```
<update>
  <contact:update
    xmlns:contact="urn:ietf:params:xml:ns:contact-1.0"
    xsi:schemaLocation="urn:ietf:params:xml:ns:contact-1.0
    contact-1.0.xsd">
    <contact:id>abcdef0704-00001</contact:id>
    <contact:chg>
      <contact:postalInfo type="loc">
        <contact:addr>
          <contact:street>Sthlmvägen 100</contact:street>
          <contact:street>Sthlmvägen 100</contact:street>
          <contact:city>Stockholm</contact:city>
          <contact:pc>11111</contact:pc>
          <contact:cc>SE</contact:cc>
        </contact:addr>
      </contact:postalInfo>
      <contact:voice x="">+46.84523500</contact:voice>
      <contact:fax x="" />
      <contact:disclose flag="1">
        <contact:voice/>
        <contact:email/>
      </contact:disclose>
    </contact:chg>
  </contact:update>
</update>
<clTRID>ABC-12345</clTRID>
</command>
</epp>
```

Example response:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <response>
    <result code="1000">
      <msg>Command completed successfully</msg>
    </result>
    <trID>
      <clTRID>ABC-12345</clTRID>
      <svTRID>54321-XYZ</svTRID>
    </trID>
  </response>
</epp>
```

7.9 Renew

Contacts cannot be renewed.

8 Host Objects

8.1 Host Rules and Policies

- Max ten ip addresses servers per host.
- For hosts outside the .se zone CoreReg will automatically be set as sponsoring client.
- hosts outside the .se zone cannot be updated (name cannot be changed and IP addresses are not needed).
- As result of the automatically assigned sponsoring client hosts outside the .se zone cannot be deleted.
- For hosts in the .se zone only IP addresses from public IP ranges are accepted. See RFC 1918, RFC 3879, RFC 3927, RFC 4193, RFC 5156, RFC 5735 and RFC6598.
- For hosts which act as name server for their parent zone glue must be provided. (This is actively checked by the EPP server). This implies that such a host must have at least one IP address associated at all times.
- Host names can consist only of small letters
- Hosts in the .se zone can only be created if the parent zone is registered
- Hosts in the .se zone can only be created by the sponsoring client of the parent zone.

Tagname/attribute	Comment
<host:name/>	Max 255 characters If the host is in the .se zone the parent domain must exist. Only lower case characters.
<host:addr/>	Multiple tags may be submitted. The ip attribute can be "v4" or "v6", if it is not given v4 is assumed.

8.2 Address update with glue record

The EPP Server strictly enforces the rule that glue record must exist for a host that is nameserver for the parent zone. This is enforced even when you do a IP-address update. The server process the remove of old IP-address before the adding of new IP-address, even if the order is sent differently in the same command.

This means that if there is a host with only one IP-address and you try to change that IP-address in one command it will be a policy violation when the old address is removed, and the command will fail

To solve this, execute the change in 2 commands. First add the new IP-address in one command and then remove the old IP-address in a new command. This way the policy is never broken.

8.3 Check

Follows RFC 5730 and RFC 5732

Example <check/> command:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <command>
    <check>
      <host:check
        xmlns:host="urn:ietf:params:xml:ns:host-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:host-1.0
        host-1.0.xsd">
        <host:name>ns1.example.se</host:name>
        <host:name>ns2.example.se</host:name>
```

```
<host:name>ns3.example.se</host:name>
</host:check>
</check>
<clTRID>ABC-12345</clTRID>
</command>
</epp>
```

Example response:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <response>
    <result code="1000">
      <msg>Command completed successfully</msg>
    </result>
    <resData>
      <host:chkData
        xmlns:host="urn:ietf:params:xml:ns:host-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:host-1.0
          host-1.0.xsd">
        <host:cd>
          <host:name avail="1">ns1.example.se</host:name>
        </host:cd>
        <host:cd>
          <host:name avail="0">ns2.example2.se</host:name>
          <host:reason>In use</host:reason>
        </host:cd>
        <host:cd>
          <host:name avail="1">ns3.example3.se</host:name>
        </host:cd>
      </host:chkData>
    </resData>
    <trID>
      <clTRID>ABC-12345</clTRID>
      <svTRID>54322-XYZ</svTRID>
    </trID>
  </response>
</epp>
```

8.4 Info

Follows RFC 5730 and RFC 5732.

Example <info/> command:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <command>
    <info>
      <host:info
        xmlns:host="urn:ietf:params:xml:ns:host-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:host-1.0
          host-1.0.xsd">
        <host:name>ns1.example.se</host:name>
      </host:info>
    </info>
    <clTRID>ABC-12345</clTRID>
  </command>
</epp>
```

Example response:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <response>
    <result code="1000">
      <msg>Command completed successfully</msg>
    </result>
    <resData>
      <host:infData
```



```

xmlns:host="urn:ietf:params:xml:ns:host-1.0"
xsi:schemaLocation="urn:ietf:params:xml:ns:host-1.0
host-1.0.xsd">
  <host:name>ns1.example.se</host:name>
  <host:roid>HOST-1234</host:roid>
  <host:status s="ok"/>
  <host:addr ip="v4">192.0.2.2</host:addr>
  <host:addr ip="v4">192.0.2.29</host:addr>
  <host:addr ip="v6">1080:0:0:0:8:800:200C:417A</host:addr>
  <host:clID>ClientY</host:clID>
  <host:crID>ClientX</host:crID>
  <host:crDate>1999-04-03T22:00:00.0Z</host:crDate>
  <host:upID>ClientX</host:upID>
  <host:upDate>1999-12-03T09:00:00.0Z</host:upDate>
</host:infData>
</resData>
<trID>
  <clTRID>ABC-12345</clTRID>
  <svTRID>54322-XYZ</svTRID>
</trID>
</response>
</epp>

```

8.5 Transfer

This command is not implemented since subordinate host objects under .se are transferred together with the domain and host objects outside .se has no sponsoring client in the registry.

8.6 Create

Follows RFC 5730 and RFC 5732. Hosts in the .se zone can only be created by the sponsoring client of the parent zone.

Example <create/> command:

```

<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <command>
    <create>
      <host:create
        xmlns:host="urn:ietf:params:xml:ns:host-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:host-1.0
        host-1.0.xsd">
          <host:name>ns1.example.se</host:name>
          <host:addr ip="v4">192.0.2.2</host:addr>
          <host:addr ip="v4">192.0.2.29</host:addr>
          <host:addr ip="v6">1080:0:0:0:8:800:200C:417A</host:addr>
        </host:create>
      </create>
      <clTRID>ABC-12345</clTRID>
    </command>
  </epp>

```

Example response:

```

<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <response>
    <result code="1000">
      <msg>Command completed successfully</msg>
    </result>
    <resData>
      <host:creData
        xmlns:host="urn:ietf:params:xml:ns:host-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:host-1.0
        host-1.0.xsd">
          <host:name>ns1.example.se</host:name>
          <host:crDate>1999-04-03T22:00:00.0Z</host:crDate>
        </host:creData>
      </resData>

```

```
<trID>
  <clTRID>ABC-12345</clTRID>
  <svTRID>54322-XYZ</svTRID>
</trID>
</response>
</epp>
```

8.7 Delete

Follows RFC 5730 and RFC 5732.

Note that host objects linked to domain objects cannot be removed.

Example <delete/> command:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <command>
    <delete>
      <host:delete
        xmlns:host="urn:ietf:params:xml:ns:host-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:host-1.0
          host-1.0.xsd">
        <host:name>ns1.example.se</host:name>
      </host:delete>
    </delete>
    <clTRID>ABC-12345</clTRID>
  </command>
</epp>
```

Example response:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <response>
    <result code="1000">
      <msg>Command completed successfully</msg>
    </result>
    <trID>
      <clTRID>ABC-12345</clTRID>
      <svTRID>54321-XYZ</svTRID>
    </trID>
  </response>
</epp>
```

8.8 Update

Follows RFC 5730 and RFC 5732.

<host:status/> is not supported

<host:name/> cannot be changed.

See 8.2 about updating hosts with glue records.

Example <update/> command:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <command>
    <update>
      <host:update
        xmlns:host="urn:ietf:params:xml:ns:host-1.0"
        xsi:schemaLocation="urn:ietf:params:xml:ns:host-1.0
          host-1.0.xsd">
        <host:name>ns1.example.se</host:name>
        <host:add>
          <host:addr ip="v4">192.0.2.22</host:addr>
        </host:add>
      </host:update>
    </update>
  </command>
</epp>
```

```
</host:add>
<host:rem>
  <host:addr ip="v6">1080:0:0:0:8:800:200C:417A</host:addr>
</host:rem>
</host:update>
</update>
<clTRID>ABC-12345</clTRID>
</command>
</epp>
```

Example response:

```
<?xml version="1.0" encoding="UTF-8" standalone="no"?>
<epp xmlns="urn:ietf:params:xml:ns:epp-1.0"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:ietf:params:xml:ns:epp-1.0 epp-1.0.xsd">
  <response>
    <result code="1000">
      <msg>Command completed successfully</msg>
    </result>
    <trID>
      <clTRID>ABC-12345</clTRID>
      <svTRID>54321-XYZ</svTRID>
    </trID>
  </response>
</epp>
```

8.9 Renew

Host objects cannot be renewed.